

Visual Broadcast System

The Just Add Power VBS Suite™ delivers a growing family of compatible A/V switching devices that allow systems integrators to build Digital Signage applications that are right-sized for the customer, with the flexibility to expand in the future as needed. Based on our popular computer lab training system technology and building on over 15 years of innovation, this twisted pair architecture gives you the flexibility to connect any number of devices together to deliver the media message in the formats demanded by today's sophisticated marketplace. From the boardroom to the classroom, in a convention center, shopping mall, or a house of worship, the VBS Suite™ provides a uniquely flexible tool for the most demanding systems integrators.

Contact us:

Just Add Power

PO Box 1064

Indian Rocks Beach, FL 33785-1064

800-615-0206

Fax: 727-517-4054

www.justaddpower.com

sales@justaddpower.com

VBS Suite™ Specifications

Controller



Total Control Console™ (VBS-ST-400A)

- 1 SETUP Mode Key
- 4 Programmable Function Keys
- 5 Output Target Select Keys
- 12 Infrared Control Keys (can save 4 sets)
- 6 Source Select Keys; 1 Broadcast Key
- 1 Darken Key; 1 Mute Key; 1 Break/Reset Key
- 1 RJ11 Port for Video Genie™ DS connection
- 9.5" W x 9.0" D x 1.75" H; 1 pound

Transmitters



Projector Connector™ Transmitter (VBS-PTP-308B)

- 1 UTP/STP VBS BUS Out Port with RJ45 termination
- 1 VGA In (Supports 1600x 1200 UXGA)
- 1 VGA Out; 1 Stereo Line Audio In; 1 Stereo Line Audio Out
- 4.5" W x 3.5" D x 1.5" H; .5 pounds
- 100-240V, 50/60 Hz, AC Adapter - .5 Amp



Video Genie™ DS0 2x10 Matrix Switcher (VBS-ST-308AS)

- 8 UTP/STP VBS BUS Out Ports with RJ45 Terminators
- 2 VGA In (Supports 1600x 1200 UXGA)
- 2 VGA Out; 2 Stereo Line Audio In
- 1 Stereo Line Audio Out; 1 Microphone In
- 1 AMP Line Out; 1 RJ11 Panel Port for Console
- 1 RS232 Interface Port for software/OEM controllers
- 11.75" W x 7.5" D x 2.25" H; 3.5 pounds
- 100-240V, 50/60 Hz, AC Adapter - 1 Amp



Video Genie™ DS1 3x10 Matrix Switcher (VBS-ST-308AV)

- 8 UTP/STP VBS BUS Out Ports with RJ45 Terminators
- 2 VGA In (Supports 1600x 1200 UXGA)
- 2 VGA Out; 2 Stereo Line Audio In
- 1 Stereo Line Audio Out; 1 Microphone In
- 1 AMP Line Out; 1 RJ11 Panel Port for Console
- 2 RS232 Interface Port; 4 RCA A/V Inputs
- 1 IR IN port; 4 IR OUT ports for IR Blasters
- 17.25" W x 8.75" D x 2.25" H; 7 pounds; Rack Mount Wings
- 100-240V, 50/60 Hz, AC Adapter - 1 Amp

Receivers



Projector Connector™ Single Receiver (VBS-PTP-108B-xxM) *xx = Cable Length

- 1 UTP/STP VBS BUS In Port
- 1 VGA Out; 1 Stereo Line Audio Out
- 4.5" W x 3.5" D x 1.5" H; .5 pounds
- 100-240V, 50/60 Hz, AC Adapter - .5 Amp
- 10M, 20M, 30M, 40M, 50M, 60M Cables



Projector Connector™ Dual Receiver (VBS-PTP-1082B-xxM) *xxM = Cable Length

- 1 UTP/STP VBS BUS In Port
- 2 VGA Out; 2 Stereo Line Audio Out
- 5.75" W x 3.75" D x 1.25" H; .5 pounds
- 100-240V, 50/60 Hz, AC Adapter - .5 Amp
- 10M, 20M, 30M, 40M, 50M, 60M Cables



Projector Connector™ Extended Receiver (VBS-PTP-300M)

- 1 UTP/STP VBS BUS In Port
- 1 VGA Out; 1 Stereo Line Audio Out
- 4.5" W x 3.5" D x 1.5" H; .5 pounds
- 100-240V, 50/60 Hz, AC Adapter - .5 Amp
- 3 Fine Tuning Knobs (Focus and Gain)
- For use with cables 200' to 1000' (300 Meters)



Projector Connector™ Pass Through Receiver (VBS-PTP-108C)

- 1 UTP/STP VBS BUS In Ports - up to 150M
- 1 UTP/STP VBS BUS Out Ports - up to 200M
- 1 VGA Out; 1 Stereo Line Audio Out
- 4.5" W x 3.5" D x 1.5" H; .5 pounds
- 100-240V, 50/60 Hz, AC Adapter - .5 Amp
- 2 Fine Tuning Knobs (Focus and Gain)
- Total BUS Cable Distance up to 1,200' (350 Meters)

Just Add Power



©Copyright 2009, Just Add Power Cardware Co., Inc.
All Rights Reserved.
All specifications subject to change without notice.

